

WHAT IS CLAIMED IS:

1. An analog signal control method comprising the steps of:

5 converting the analog signal to a digital signal;
 performing an arithmetic processing of the digital
signal to generate a control signal for controlling the
analog signal;

10 delaying the analog signal corresponding to a latency
caused by the generation of the control signal to generate
a delayed analog signal; and

 controlling the delayed analog signal in accordance
with the control signal.

15 2. The analog signal control method according to claim 1,
wherein:

 the step of converting includes sampling the analog
signal at a predetermined timing to generate a sampling
value;

20 the step of generating a control signal includes
generating the control signal in accordance with the
sampling value; and

 the step of delaying includes delaying the analog
signal to control the analog signal in accordance with the
25 control signal, the analog signal having a sampling value
corresponding to the predetermined sampling timing.

3. The analog signal control method according to claim 1,
wherein:

30 the step of converting includes sampling the analog
signal at a predetermined timing to generate a sampling
value;

 the step of generating a control signal includes

generating the control signal in accordance with the sampling value; and

the step of delaying includes delaying the analog signal by the latency or more to control the analog signal in accordance with the control signal, the analog signal having a sampling value produced by sampling the analog signal at a timing previous to the predetermined sampling timing.

4. The analog signal control method according to claim 1, wherein:

the step of converting includes sampling the analog signal at a plurality of predetermined timings to generate a plurality of sampling values;

the step of generating a control signal includes calculating the plurality of sampling values to generate the control signal; and

the step of delaying delays the analog signal to control the analog signal in accordance with the control signal, the analog signal having a sampling value corresponding to an arbitrary sampling timing.

5. The analog signal control method according to claim 1, wherein:

the step of converting includes sampling the analog signal at a plurality of predetermined timings to generate a plurality of sampling values;

the step of generating a control signal includes calculating the plurality of sampling values to generate the control signal; and

the step of delaying includes delaying the analog signal to control the analog signal in accordance with the control signal, the analog signal having a sampling value

produced by sampling the analog signal at a timing previous to each sampling timing.

6. An analog signal control method comprising the steps
5 of:

converting the analog signal to a digital signal;
performing an arithmetic processing of the digital
signal to generate a control signal for controlling the
analog signal;

10 delaying the analog signal corresponding to a latency
caused by the generation of the control signal in
synchronism with a clock signal to generate a delayed
analog signal; and

controlling the delayed analog signal in accordance
15 with the control signal.

7. An analog signal controller comprising:

an ADC for analog-to-digital converting an analog
signal to generate a digital signal;

20 a digital arithmetic circuit connected to the ADC for
performing an arithmetic processing of the digital signal
to generate a control signal for controlling the analog
signal;

a delay circuit for receiving the analog signal, and
25 delaying the analog signal corresponding to a latency
caused by the ADC and the digital arithmetic circuit to
generate a delayed analog signal; and

an analog control circuit connected to the digital
arithmetic circuit and the delay circuit for controlling
30 the delayed analog input signal in accordance with the
control signal.

8. The analog signal controller according to claim 7,

wherein:

the analog signal controller operates in accordance with a clock signal; and

the delay circuit includes a pair of switches which
5 operate complementary to each other in synchronism with the clock signal, and delays the analog signal by switching the pair of switches.

9. The analog signal controller according to claim 8,
10 wherein:

the delay circuit includes a capacitor connected between a node between the pair of switches and a ground.

10. The analog signal controller according to claim 8,
15 wherein:

the delay circuit includes a plurality of delay stages connected in series, each of the delay stages including the pair of switches;

the ADC samples the analog signal to generate a
20 sampling value; and

the delay circuit further includes a selector circuit for selecting the number of connected ones of the plurality of delay stages in accordance with the sampling value of the analog signal.

11. The analog signal controller according to claim 10,
25 wherein:

each of the plurality of delay stages includes a capacitor connected between a node between the pair of
30 switches and a ground.

12. The analog signal controller according to claim 7,
wherein:

the delay circuit includes a capacitor for delaying the analog signal; and

the capacitor has a capacitance value which is set such that the analog signal is delayed corresponding to the latency.

13. The analog signal controller according to claim 7, wherein:

the delay circuit includes a variable capacitor for delaying the analog signal; and

the variable capacitor is set such that the analog signal is delayed corresponding to the latency.

14. An automatic gain controller comprising:

a first control loop for receiving an analog signal to generate a control signal for setting a predetermined gain for use in amplifying the analog signal;

a delay circuit for receiving the analog signal, and delaying the analog signal corresponding to a latency caused by the first control loop to generate a delayed analog signal; and

a GCA connected to the delay circuit and the first control loop for amplifying the delayed analog signal in accordance with a predetermined gain set by the control signal to generate an amplified analog signal.

15. An automatic gain controller comprising:

a first control loop, the first control loop including:

a first GCA for amplifying the analog signal in accordance with a first predetermined gain to generate a first amplified analog signal;

an ADC connected to the first GCA for analog-to-

digital converting the first amplified analog signal to generate a digital signal;

an error calculating circuit connected to the ADC for calculating an error between a target value which is set
5 such that the first amplified analog signal substantially covers a full range for an input level of the ADC, and the digital signal to generate an error digital signal in accordance with the error; and

a DAC connected to the error calculating circuit for
10 digital-to-analog converting the error digital signal to generate a control signal for setting a second predetermined gain;

a delay circuit for delaying the analog signal corresponding to a latency occurring in the first control
15 loop to generate a delayed analog signal; and

a second GCA connected to the delay circuit and the first control loop for amplifying the delayed analog signal in accordance with the second predetermined gain set by the control signal to generate a second amplified analog
20 signal.

16. The automatic gain controller according to claim 15, further comprising:

a control loop connected to the second GCA for
25 calculating an error for the second amplified analog signal.

17. The automatic gain controller according to claim 15, wherein:

30 the AGC operates in accordance with a clock signal; and

the delay circuit includes a delay stage for delaying the analog signal in synchronism with the clock signal.

18. The automatic gain controller according to claim 17,
wherein:

the delay stage is one of a plurality of delay stages
5 connected in series; and

the delay circuit further includes a selector circuit
for selecting the number of connected ones of the plurality
of delay stages in accordance with a predicable waveform of
the analog signal.

19. An automatic gain controller comprising:

a first ADC for sampling an analog signal to generate
a first plurality of sampling values, the first ADC
generating a first digital signal in accordance with the
15 first plurality of sampling values;

a first average processing circuit connected to the
first ADC for calculating an average value of the first
plurality of sampling values in accordance with the first
digital signal to generate a first average value signal
20 indicative of the calculated average value;

a first gain selector circuit connected to the first
average processing circuit for selecting a first gain for
controlling the analog signal in accordance with the
average value of the first average value signal, and
25 generating a first control signal in accordance with the
selected first gain;

a first delay circuit for receiving the analog signal,
and delaying the analog signal corresponding to a first
latency occurring in the first ADC, the first average
30 processing circuit, and the first gain selector circuit to
generate a first delayed analog signal; and

a gain switching amplifier connected to the first
delay circuit and the first gain selector circuit for

amplifying the first delayed analog signal in accordance with the first gain selected by the first control signal to generate a first amplified analog signal.

5 20. The automatic gain controller according to claim 19, further comprising:

a second AGC connected to the first gain switching amplifier for amplifying the first amplified analog signal, wherein the second AGC includes:

10 a second ADC for sampling the first amplified analog signal to generate a second plurality of sampling values, the second ADC generating a second digital signal in accordance with the second plurality of sampling values;

15 a second average processing circuit connected to the second ADC for calculating an average value of the second plurality of sampling values in accordance with the second digital signal to generate a second average value signal indicative of the calculated average value;

20 a second gain selector circuit connected to the second average processing circuit for selecting a second gain for controlling the first amplified analog signal in accordance with an average value of the second average value signal, and generating a second control signal in accordance with the selected second gain;

25 a second delay circuit for receiving the first amplified analog signal, and delaying the first amplified analog signal corresponding to a second latency occurring in the second ADC, the second average processing circuit, and the second gain selector circuit to generate a second
30 delayed analog signal; and

a second gain switching amplifier connected to the second delay circuit and the second gain selector circuit for amplifying the second delay analog signal in accordance

with the second gain selected by the second control signal to generate a second amplified analog signal.

21. The automatic gain controller according to claim 19,
5 further comprising:

a control loop connected to the first gain switching amplifier for calculating an error of the first amplified analog signal.

10 22. The automatic gain controller according to claim 19, wherein:

the first average processing circuit changes sampling numbers of the first plurality of sampling values in accordance with a predicted waveform of the analog signal
15 when the waveform of the analog signal is predictable.

23. The automatic gain controller according to claim 19, wherein:

the first average processing circuit changes sampling
20 positions of the first plurality of sampling values in accordance with a predicted waveform of the analog signal when the waveform of the analog signal is predictable.